

General conditions
3phase SPWM

V_{GEon}	=	15 V
V_{GEoff}	=	-15 V
R_{gon}	=	16 Ω
R_{goff}	=	16 Ω

Figure 1 IGBT

Typical average static loss as a function of output current

$$P_{loss} = f(I_{out})$$



At
 $T_j = 150 \text{ } ^\circ\text{C}$
 $M_i \cdot \cos\phi$ from -1 to 1 in steps of 0,2

Figure 2 FWD

Typical average static loss as a function of output current

$$P_{loss} = f(I_{out})$$




At
 $T_j = 150 \text{ } ^\circ\text{C}$
 $M_i \cdot \cos\phi$ from -1 to 1 in steps of 0,2

Figure 3 IGBT

Typical average switching loss as a function of output current

$$P_{loss} = f(I_{out})$$


At
 $T_j = 150 \text{ } ^\circ\text{C}$


DC link = 600 V

 f_{sw} from 2 kHz to 16 kHz in steps of factor 2

Figure 4 FWD

Typical average switching loss as a function of output current


$$P_{loss} = f(I_{out})$$


At
 $T_j = 150 \text{ } ^\circ\text{C}$


DC link = 600 V

 f_{sw} from 2 kHz to 16 kHz in steps of factor 2


flow90PACK 1 2nd gen Output Inverter Application 1200V/35A

Figure 5 Phase



At
 $T_j = 150 \text{ } ^\circ\text{C}$
 DC link = 600 V
 $f_{sw} = 4 \text{ kHz}$
 T_h from 60 °C to 100 °C in steps of 5 °C

Figure 6 Phase


At
 $T_j = 150 \text{ } ^\circ\text{C}$
 DC link = 600 V
 $Mi \cdot \cos \phi = 0,8$
 T_h from 60 °C to 100 °C in steps of 5 °C


Figure 7 Phase


At
 $T_j = 150 \text{ } ^\circ\text{C}$
 DC link = 600 V
 $T_h = 80 \text{ } ^\circ\text{C}$

Figure 8 Phase



At
 $T_j = 150 \text{ } ^\circ\text{C}$
 DC link = 600 V
 T_h from 60 °C to 100 °C in steps of 5 °C
 $Mi = 0$

Figure 9 Inverter

Typical available peak output power as a function of heatsink temperature
 $P_{out}=f(T_h)$



At
 $T_j = 150$ °C
 DC link = 600 V
 $M_i = 1$
 $\cos \varphi = 0,80$
 f_{sw} from 2 kHz to 16 kHz in steps of factor 2

Figure 10 Inverter

Typical efficiency as a function of output power
 $\text{efficiency}=f(P_{out})$


At
 $T_j = 150$ °C
 DC link = 600 V
 $M_i = 1$
 $\cos \varphi = 0,80$
 f_{sw} from 2 kHz to 16 kHz in steps of factor 2

Figure 11 Inverter

Typical available overload factor as a function of motor power and switching frequency
 $P_{peak} / P_{nom}=f(P_{nom}, f_{sw})$


At
 $T_j = 150$ °C
 DC link = 600 V
 $M_i = 1$
 $\cos \varphi = 0,8$
 f_{sw} from 1 kHz to 16kHz in steps of factor 2
 $T_h = 80$ °C
 Motor eff = 0,85